

## PART NUMBER DETAILS

2 Gang Plate with Mortise Cylinder Bracket - uses **85dB Sounder**

**LDA9603-MOM** - Momentary Key Switch—Reset an alarm only

**LDA9603-MNT** - Maintained Key Switch—Push On to Bypass or Disarm and Push Off to Rearm

2 Gang Plate with Mortise Cylinder Bracket - uses **95dB sounder**

**LDA9613-MOM** - Momentary Key Switch—Reset an alarm only

**LDA9613-MNT** - Maintained Key Switch—Push On to Bypass or Disarm and Push Off to Rearm

## OVERVIEW

The Local Door Alarm (LDA) monitors door contacts, motion sensors, and access control devices such as card reader systems or keypads to determine and annunciate the status of a controlled door. A sounder alerts area personnel of a door control violation, and the building alarm system is notified with alarm relay contacts. The Warning Alarm feature reduces nuisance alarms by sounding a local alarm a few seconds before a Door Held Alarm.

## FEATURES

- ◇ Local Warning Alarm
- ◇ Door Held Alarm
- ◇ Forced Door Alarm
- ◇ Supervised Door Contact Monitoring
- ◇ Remote Alarm Bypass
- ◇ Request to Exit
- ◇ Request to Enter
- ◇ Adjustable Time Delays
- ◇ Automatic Alarm Reset Delay
- ◇ Access and Secure LED's
- ◇ Double Gang Box Mounting
- ◇ Mortise Cylinder Bracket
- ◇ Other Colors Available



**(Mortise Cylinder Lock Not Included)**

The LDA was developed with the intention of reducing nuisance alarms caused by improper door usage, as well as providing flexible door alarm monitoring. Several field selectable operating modes allow system integrators to utilize a single type of door alarm to handle a large variety of alarm applications.

---

## CUT SHEET CONTINUED

---

### TECHNICAL SPECIFICATIONS

*Note: these specifications are subject to change*

<b>Power</b>	12 - 24 VAC/VDC @ 250 max.
<b>Inputs</b>	1 Normally Closed fully supervised door input. (1K ohm = closed, 2K ohm = open, else = supervision fault). Supervision monitoring may be disabled at installation. 3 Access Control inputs: Remote N/O alarm bypass, N/O or N/C request to exit shunt, and fail-safe or fail secure lock voltage monitoring (12 - 24 VAC/VDC).
<b>Outputs</b>	1 Normally Closed (NC) Entry Alarm Relay rated @ 1/2 A. Opens with Forced Door Alarm or Door Held Alarm after Lock Voltage shunt. 1 Normally Closed (NC) Exit Alarm Relay rated @ 1/2 A. Opens with Door Held Alarm after Request To Exit shunt. Alarm sounder @ 85dB (9603) or 95db (9613). Pulsing tones indicate Warning Alarm, and constant tone indicates Door Violation Alarm. Green LED indicates access mode, Red LED indicates armed.
<b>Time Delays</b>	Access delay - adj. 0 - 60 sec. Shunts the alarm function for the duration of the delay Warning delay - adj. 0 - 60 sec. Sets the duration of the Warning Alarm. Alarm automatic reset delay - adj. 0 - 60 sec. Sets the duration of an alarm if the Automatic Reset feature is enabled.
<b>Field Options</b>	Forced Door Alarm disable. Supervision monitoring disable. N/O or N/C Request To Exit monitoring. Fail-safe or fail-secure Lock Voltage Monitoring. Alarm Automatic Reset disable.
<b>Key Switch</b>	Mortise Cylinder Lock is not included. Recommended Mortise Cylinder is 1 1/8", 6 Pin, Kaba-Ilco part # 7186-SC-5 or equivalent. Mounting Bracket provided with momentary <u>or</u> maintained switch (see part numbers)
<b>Mounting</b>	2 Gang, 2-1/2 inch deep electrical box.
<b>Terminal Strips</b>	Fixed Terminal strips accept up to 16 AWG wires.

### LOCAL DOOR ALARM OPERATION OPTIONS

Add the designated suffix to the end of the model number for these operational features.

BP	Standard Operation as noted on the specification sheet. RE1- Bypass Status, RE2- Alarm Status
INT	Same operation as noted on the specification sheet except for relay operation. RE1-N/C Forced Door Alarm, RE2- Door Held Alarm
HS5	For use at Card In/ Card Out doors while allowing Free Exit during emergencies. Lock Voltage Shunt Input resets an alarm. Refer to HS5 Application note. RE1- N/C Forced Door and Door Held Alarm, RE2- N/C Delayed Forced Door Alarm remains closed until 20 seconds after a Forced Door Alarm to allow time to reset alarm prior to transmitting an alarm to the monitoring system.

---

**KOUBA & ASSOCIATES, INC.**  
**4040 FM 535**  
**BASTROP, TEXAS 78602**

**PHONE: 512.303.5033**  
**TOLL FREE: 877-873-8242**  
**WWW.KOUBASYSTEMS.COM**

---