

## OVERVIEW

Our basic pedestrian counting system, the LDA-CTR uses a Local Door Alarm circuit board with an internal doorway counting program, a set of sensors for each door, and one display unit to monitor and count pedestrian traffic through doorways or other passageways.

## FEATURES

- ◇ Computes and displays current occupancy level
- ◇ Tracks and displays entry total
- ◇ LCD display w/ backlight button
- ◇ Reset key switch
- ◇ Units can be linked to provide single counter output for multiple doors
- ◇ Available as free-standing or doorway-mounted units



## OPERATION

**ENTRY:** When a person walks through the sensing area in the entry direction, the output relay for the LDA-CTR sends an entry signal to the display module. Both the Total In and Occupancy Count are incremented.

**EXIT:** When a person walks through the sensing area in the exit direction, the output relay for the LDA-CTR sends an exit signal to the Occupancy Display Module. The Occupancy count is decremented; the Total In Count does not receive a signal.

**LINKED DOORWAYS:** Each LDA-CTR has a Link Input, which can be connected through a Link Module to the relay outputs of a previous LDA-CTR. The link passes the entry and exit signals through the LDA-CTR circuit board. This allows several doorways to be monitored and counted by a single display unit.

## TECHNICAL SPECIFICATIONS

<b>POWER</b>	12 VDC @ 100 ma per doorway.
<b>INPUTS</b>	Reset Key Switch. Entry Sensor Inputs for each doorway. Exit Sensor Inputs for each doorway.
<b>OUTPUTS</b>	Red Lion Controls Model # CUB2LU00. Total In Count Display Module or Occupancy Count Display Module.
<b>DIMENSIONS</b>	Doorway Sensor Housing 1.25" W x 12" H x 1.25" D Post Sensor Housing 2" x 3" x 30" (post), 12" x 12" x 3" (footing) Display Unit Standard 2-Gang or 3-Gang Electrical Plate